

PRODUCT SPECIFICATION

FIBER CLEANING KIT

INTRODUCTION

LUX's Fiber Optic Cleaner for simplex connections includes a dry cloth cleaner especially design for cleaning single fiber connectors. Designed as an adapter, the dust cap of the cleaner acts as an adapter for cleaning unmated connectors. The LUX Fiber Optic Cleaner for simplex connections is simple, easy to use, and highly effective at removing oil and dust contaminants which can inhibit optical performance.

SMART CLEANER 1.25

Working with LC connectors often means technicians are dealing with a high volume of connectors, it is difficult to get in between to service and clean.

LUX's Fiber Optic Cleaner is specially made with LC connectors with its thin, extendable shaft that can easily get in between hard to reach areas.

Compatible Connector: MU & LC



SMART CLEANER 2.50

Work well with SC, FC, ST, and E-2000 connectors, this instrument cleans the ferrule end faces by removing dust, oil, and other debris without nicking or scratching the end face.

Compatible Connector: SC & FC & ST & E-2000

SMART CLEANER MPO

Fitted with a tip just for the MPO connector, LUX's Fiber Optic Cleaner is designed for multi fiber connector making cleaning easy by effortlessly removing debris from the entire end faces at once. All of LUX's Fiber Optic Cleaners are designed to clean both exposed jumper ends and connectors in adapters.

Compatible Connector:
MPO Connectors, MTP Connectors Plug and Port




FEATURES

- Easy pushing motion engages connector and initiates cleaner
- Disposable with 750+ cleanings per unit (FIBER CLEANING KIT – LC & MU & SC & FC & ST & E2000)
- Disposable with 600+ cleanings per unit (FIBER CLEANING KIT – MPO)
- Made from antistatic resin
- Cleaning densely stranded microfibers and debris free
- Extendable tip reaches recessed connectors
- Cleaning system can rotate 180° for full sweep
- Audible click sound when engaged

The information and specification in this document are subjected to change without notice

ORDERING PART NUMBER

Example: FCK-SS-125 = Smart Cleaner 1.25 (Cleaning Unit)



The information and specification in this document are subjected to change without notice